RESISTOR **FLANGE MOUNT 150 WATT**





DATA SHEET PART SERIES: 31A7021XXF

SHEET 1 OF 2 Dwg 31A7021F

EN 13-3527

FEATURES APPLICATIONS

Tab Launch Broadcast


High Power High Power Filters Integrated Heat Sink **High Power Amplifiers**

Low Capacitance Isolators Easy Installation Military

Wide Resistance Range Instrumentation

GENERAL DESCRIPTION

EMC Technology offers the widest selection of flange mount resistors worldwide. High power flange components offer excellent performance and the convenience of bolt on installation.



ORDERING INFORMATION

Part Identifier:

31A7021XXF

└ Tolerance Resistance Value

SPECIFICATIONS

1.0 ELECTRICAL

7 - 250 OHMS Resistance Range:

Resistance Tolerance: ±5% standard 1% and 2% available

Typical Capacitance: 1.38 pF

Input Power CW: 150 watts @ 100°C heat sink, derated linearly to zero power at 150°C

Peak Power: 1500 watts (based on 10us pulse width and 1% duty cycle)

2.0 ENVIRONMENTAL

Operating Temperature: -55°C to +150°C Non-operating Temperature: -65°C to +150°C Temperature Coefficient: +/-200 PPM / °C max

3.0 MARKING

Unit Marking: Logo and Part Number, legibility and permanency per MIL-STD-130

4.0 QUALITY ASSURANCE

Visual and Mechanical Inspection: Per 824W107

100% DC Resistance Check DC Resistance Check:

Data Retention: Standard

5.0 PACKAGING

Standard Packaging: Tray

Cage Codes: 24602 / 2Y194 www.emc-rflabs.com • +1 772-286-9300 smiths microwave Form 423F104 Rev-

RESISTOR FLANGE MOUNT 150 WATT





DATA SHEET PART SERIES: 31A7021XXF

SHEET 2 OF 2 Dwg 31A7021F EN 13-3527 Revision-


6.0 MECHANICAL


Substrate Material: Aluminum Nitride

Resistive Film: Thin Film
Cover Material: Alumina

Tab Material:Beryllium CopperTab Finish:Silver PlatedFlange Material:CopperFlange Finish:Nickel

Metric Dimensions: Provided for reference only





Unless Otherwise Specified: TOLERANCE: X.XX = ± 0.02 X.XXX = ± 0.010

smiths microwave

Form 423F104 Rev-

Cage Codes: 24602 / 2Y194
Specifications are Subject to Change Without Notice